June 2006

FFB20UP20DN 10A, 200V Ultrafast Dual Rectifiers

FAIRCHILD

SEMICONDUCTOR® FFB20UP20DN

10A, 200V Ultrafast Dual Rectifiers

Features

- High Reverse Voltage : V_{RRM} = 200V
- Avalanche Energy Rated
- Planar Construction

Applications


- Output Rectifiers
- Switching Mode Power Supply
- Free-wheeling diode for motor application
- Power switching circuits


Description

The FFB20UP20DN is an ultrafast rectifier. It has a low forward voltage drop and is a silicon nitride passivated ionimplanted epitaxial planar construction.

This device is intended for use as a freewheeling/clamping rectifier in a variety of switching power supplies and other power switching applications. Its low stored charge and hyperfast recovery minimize ringing and electrical noise in many power switching circuits, thus reducing power loss in the switching transistors.

Pin Assignments





1. Anode 2. Cathode 3. Anode

Absolute Maximum Ratings T_C = 25°C unless otherwise noted

Symbol	Parameter	Ratings	Units	
V _{RRM}	Peak Repetitive Reverse Voltage		200	V
V _{RWM}	Working Peak Reverse Voltage		200	V
V _R	DC Blocking Voltage		200	V
I _{f(avg)}	Average Rectified Forward Current	@ T _C = 155°C	10	А
I _{FSM}	Non-repetitive Peak Surge Current 60Hz Single Half-Sine Wave		100	А
T _{J,} T _{STG}	Operating Junction and Storage Temperature		-55 to +175	°C

Thermal Characteristics T_C = 25°C unless otherwise noted

Symbol	Parameter	Мах	Units
$R_{\theta JC}^{1}$	Maximum Thermal Resistance, Junction to Case	3.5	°C/W

Package Marking and Ordering Information

Device Marking	Device	Package	Reel Size	Tape Width	Quantity
F20UP20DN	F20UP20DN	TO-263	13"	24mm	800

Symbol	Parameter Min.		Тур.	Max	Units	
${\rm F}^2$	I _F = 10A I _F = 10A	$T_{C} = 25^{\circ}C$ $T_{C} = 150^{\circ}C$	-	-	1.15 1.0	V V
R ²	V _R = 200V V _R = 200V	$T_{C} = 25^{\circ}C$ $T_{C} = 150^{\circ}C$	-	-	10 250	μΑ μΑ
rr	I_F =1A, di/dt = 200A/µs, V _{CC} = 130V I_F =10A, di/dt = 200A/µs, V _{CC} = 130V	$T_{C} = 25 \ ^{\circ}C$ $T_{C} = 25^{\circ}C$	-	15 27	25 40	ns ns
a b Q _{rr}	I _F =10A, di/dt = 200A/µs, V _{CC} = 130V	$T_{C} = 25^{\circ}C$ $T_{C} = 25^{\circ}C$ $T_{C} = 25^{\circ}C$	- -	21 6 50	- - -	ns ns nC
N _{AVL}	Avalanche Energy (L = 20mH)	•	10	-	-	mJ
Rth_jc value is spec Pulse: Test Pulse w V _{GE} AMPLITUDE A R _G CONTROL dlp/	idth = 300S, Duty Cycle = 2%					

trr TEST CIRCUIT

L R

> +٩ V_{DD}

V_{DD}


- °

m


CURRENT SENSE

$$\begin{split} &I_{MAX} = 1A \\ &L = 20mH \\ &R < 0.1\Omega \\ &E_{AVL} = 1/2LI^2 \left[V_{R(AVL)} / (V_{R(AVL)} - V_{DD}) \right] \\ &Q_1 = IGBT \left(BV_{CES} > DUT \, V_{R(AVL)} \right) \end{split}$$

Q1




trr WAVEFORMS AND DEFINITIONS




AVALANCHE CURRENT AND VOLTAGE WAVEFORMS

AVALANCHE ENERGY TEST CIRCUIT

DUT



FFB20UP20DN Rev. A



FFB20UP20DN Rev. A

www.fairchildsemi.com

TRADEMARKS

The following are registered and unregistered trademarks Fairchild Semiconductor owns or is authorized to use and is not intended to be an exhaustive list of all such trademarks.

ACEx™ FACT Quiet Series™ ActiveArray™ GlobalOptoisolator™ GTO™ Bottomless™ Build it Now™ HiSeC™ CoolFET™ I²C[™] i-Lo™ CROSSVOLT™ DOME™ ImpliedDisconnect[™] EcoSPARK™ IntelliMAX™ E²CMOS™ ISOPLANAR™ EnSigna™ LittleFET™ FACT™ MICROCOUPLER™ $\mathsf{FAST}^{\mathbb{R}}$ MicroFET™ FASTr™ MicroPak™ FPS™ MICROWIRE™ FRFET™ MSX™ MSXPro™ Across the board. Around the world.™

 OCX^{TM} S $OCXPro^{TM}$ S $OCXPro^{TM}$ S $OPTOLOGIC^{\textcircled{B}}$ S $OPTOPLANAR^{TM}$ S $PACMAN^{TM}$ S POP^{TM} S $Power247^{TM}$ S $PowerEdge^{TM}$ S $PowerSaver^{TM}$ S $PowerSaver^{TM}$ S $PowerSaver^{TM}$ S $QFET^{\textcircled{B}}$ T $QTOptoelectronics^{TM}$ T $Quiet Series^{TM}$ T $RapidConfigure^{TM}$ T $RapidConnect^{TM}$ T $ScalarPump^{TM}$ L

SILENT SWITCHER[®] SMART START[™] SPM[™] Stealth[™] SuperFET[™] SuperSOT[™]-3 SuperSOT[™]-6 SuperSOT[™]-6 SuperSOT[™]-8 SyncFET[™] TCM[™] TinyBoost[™] TinyBoost[™] TinyBuck[™] TinyPWM[™] TinyPWM[™] TinyPWM[™] TinyPower[™] TinyLogic[®] TINYOPTO[™] TruTranslation[™] UHC[™] UniFET™ UltraFET[®] VCX™ Wire™

PowerTrench [®]	TCM™
QFET [®]	TinyBoost™
QS™	TinyBuck™
QT Optoelectronics™	TinyPWM™
Quiet Series™	TinyPower™
RapidConfigure™	TinyLogic [®]
RapidConnect™	TINYOPTO™
µSerDes™	TruTranslation™
ScalarPump™	UHC™

DISCLAIMER

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION, OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS. THESE SPECIFICATIONS DO NOT EXPAND THE TERMS OF FAIRCHILD'S WORLDWIDE TERMS AND CONDITIONS, SPECIFICALLY THE WARRANTY THEREIN, WHICH COVERS THESE PRODUCTS.

LIFE SUPPORT POLICY

The Power Franchise[®] Programmable Active Droop[™]

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF FAIRCHILD SEMICONDUCTOR CORPORATION.

As used herein:

 Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, or (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in significant injury to the user. 2. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

Datasheet Identification	Product Status	Definition		
Advance Information	Formative or In Design	This datasheet contains the design specifications for product development. Specifications may change in any manner without notice.		
Preliminary	First Production	This datasheet contains preliminary data, and supplementary data will be published at a later date. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.		
No Identification Needed	Full Production	This datasheet contains final specifications. Fairchild Semiconductor reserves the right to make changes at any time without notice to improve design.		
Obsolete	Not In Production	This datasheet contains specifications on a product that has been discontinued by Fairchild semiconductor. The datasheet is printed for reference information only.		

PRODUCT STATUS DEFINITIONS Definition of Terms